

Ixia Power Chassis

DUAL AC OR DC POWER SUPPLY FOR TAPS AND BYPASSES

ELIMINATE CLUTTER FROM MULTIPLE SEPARATE POWER SUPPLIES

This dual AC or DC input power supply provides 24 or 16 DC power leads in a rack-mountable 1U chassis. The power supply supports 24/16 single or 12/8 redundant power connections compatible with Ixia's rack-mountable Ixia 10/100/1G Copper Tap, Ixia Copper Port Aggregator, and some Gigabit taps.

Compatible with 100-230 VAC input, the Ixia Power Chassis delivers 350 Watts of power to Ixia 12/8 VDC devices worldwide. A -48 VDC powered model is also available.



HIGHLIGHTS

- Powers 24/16 single or 12/8 redundant power connections
- Two 12/8 lead connection sets support easy pairing for power redundancy
- Universal power enables worldwide deployment
- LED indicators show redundant power status
- Accepts 110 and 220 VAC input, DC input model also available
- Strain-relief cable control
- Incorporates 19" rack mount frame for easy installation
- Two 12/8-lead connection sets support easy pairing for power redundancy
- Two meter DC power leads for easy connection

SPECIFICATIONS

Operating	<ul style="list-style-type: none"> • Operating Temperature: 0°C to 40°C • Storage Temperature: -20°C to 85°C • Relative Humidity: 10% min, 95% max, non-condensing
Electrical	<ul style="list-style-type: none"> • AC Input: 85-264VAC, 47-63Hz, 5A Max @ 115 VAC, 2.5A Max @ 230 VAC • DC Input: -48VDC nominal, -36 to -72VDC, 12.2A Max @ 36VDC, 5.8A Max @ 72VDC • Output: 12V, 3.6A per lead (AC model), 2.4A per lead (DC model)

SPECIFICATIONS	
Mechanical	<ul style="list-style-type: none"> • Dimensions: 1.75" high x 12.5" deep x 17" wide • Connector Type: DC Jack barrel type connector w/ 2.5 mm ID
Certifications	CE, VCCI, C-Tick, and MET (USA safety) certified Fully RoHS and WEEE compliant

ORDERING INFORMATION

PWR12-350

Power Chassis, 110/240V AC in, 12V DC out, 1U, 350W, Supplies 12 units with up to 1.5A.
For use with TP-CU3 and I3BP-CU3 taps/bypass. (955-8052)

PWR12-350-8L

Power Chassis, 110/240V AC in, 12V DC out, 1U, 350W, Supplies 8 units with up to 3.3A.
For use with TP-CU3, TP-CU3-ZD*, and I3BP-CU3 taps/bypass. (955-8055)

PWR12-350-DC

Power Chassis, -48V DC in, 12V DC out, 1U, 350W, Supplies 12 units with up to 1.5A.
For use with TP-CU3 and I3BP-CU3 taps/bypass. (955-8056)

* TP-CU3-ZD is supported by PWR12-350-8L only, and not PWR12-350-DC.

All products include a 1-year manufacturer's warranty. An additional extended warranty plan may also be purchased.

IXIA WORLDWIDE HEADQUARTERS

26601 AGOURA ROAD
CALABASAS, CA 91302

(TOLL FREE NORTH AMERICA)

1.877.367.4942

(OUTSIDE NORTH AMERICA)

+1.818.871.1800

(FAX) 818.871.1805

www.ixiacom.com

IXIA EUROPEAN HEADQUARTERS

IXIA TECHNOLOGIES EUROPE LTD
CLARION HOUSE, NORREYS DRIVE
MAIDENHEAD SL6 4FL
UNITED KINGDOM

SALES +44.1628.408750

(FAX) +44.1628.639916

IXIA ASIA PACIFIC HEADQUARTERS

101 THOMSON ROAD,
#29-04/05 UNITED SQUARE,
SINGAPORE 307591

SALES +65.6332.0125

(FAX) +65.6332.0127